

NTH-146

PAR20 Front Loading Gimbal Ring

Lamp: 50W PAR20 max.

Type

Project

Catalog No.

Notes

PRODUCT DESCRIPTION

Line voltage PAR adjustable gimbal ring affixed to socket cup to allow lamp installation and removal from the front of the fixture, rather than having to clip the lamp into a ring. A steel yoke holds the gimbal ring in place and allows for full lateral aiming adjustment with high friction hold on vertical angle.

FEATURES

- Deep drawn steel socket cup housing for high strength and rigidity
- Heat resistant Teflon coated wire lead
- Low profile gimbal ring with minimal profile
- Adjustable yoke for custom aiming
- High-strength stainless steel electrical contacts
- One or two circuit track capable
- Accepts LED lamps

CONSTRUCTION

Housing Socket Cup: 0.03" Drawn steel cup contains socket, and two tempered stainless steel springs that secure an extension cover for shielding the base and neck of any lamp source. Extension can also be removed if desired.

Gimbal Ring: 0.030" Baked enamel finished steel ring with dual brackets spot welded to socket cup enclosure.

Yoke: 0.085" Rigid steel "wishbone" yoke connects fixture housing to electrical contact head. Dual semi tubular rivets and friction washers provide secure hold for vertical angle.

ELECTRICAL

Voltage: 120V input

Socket: Medium base

Lamp: 50W PAR20 max. (not included)

FINISH

Available in black and white finishes.

ONE/TWO CIRCUIT CONVERSION

Positive contact (opposite neutral and ground contacts) is preset to "down" position at factory but may be raised to the higher position to install onto the second circuit of Nora Lighting NT- 2300 series two-circuit track.

LABELS AND LISTINGS

UL Listed




PRODUCT IMAGES AND DIMENSIONS



NTH-146B
Black
Front Loading Gimbal



NTH-146W
White
Front Loading Gimbal



PAR20 Front Loading Gimbal Ring

Catalog No.	Finishes	Style
NTH-146	B = Black	(blank) = H-style
	W = White	/J = J-style
		/L = L-style

Example: **NTH-146B** = PAR20 Front Loading Gimbal Ring, Black Finish, H-Style Adapter